

PRODUCT-DETAILS

PSR6-600-70

PSR6-600-70 Softstarter



General Information

| | |
|-------------------------|---|
| Global Commercial Alias | PSR6-600-70 |
| Extended Product Type | PSR6-600-70 |
| Product ID | 1SFA896104R7000 |
| ABB Type Designation | PSR6-600-70 |
| EAN | 7320500338209 |
| Catalog Description | PSR6-600-70 Softstarter |
| Long Description | Softstarter PSR6-600-70 for max 600V main voltage and 100-240V 50/60Hz control supply voltage |

Ordering

| | |
|------------------------|----------|
| Minimum Order Quantity | 1 piece |
| Customs Tariff Number | 85044090 |

Popular Downloads

| | |
|-----------------------------------|-----------------|
| Data Sheet, Technical Information | 1SFC132005C0201 |
| Instructions and Manuals | 1SFC132030M0001 |

Dimensions

| | |
|-------------------------------|------------|
| Product Net Width | 45.000 mm |
| Product Net Height | 140.000 mm |
| Product Net Depth / Length | 114.000 mm |
| Product Net Weight | 0.4 kg |

Technical

| | |
|---|---|
| Rated Operational Voltage | 208 ... 600 V AC |
| Rated Control Supply Voltage (U_s) | 100 ... 240 V AC |
| Rated Control Circuit Voltage (U_c) | 50 Hz / 60 Hz 100 ... 240 V AC |
| Rated Frequency (f) | Main Circuit 50/60 Hz Control Supply 50/60 Hz |
| Rated Operational Power - In-Line Connection (P_e) | (230 V) 1.5 kW (400 V) 3 kW (500 V) 4 kW |
| Rated Operational Current - In-Line Connection (I_e) | 6.8 A |
| Service Factor Percentage | 100 % |
| Overload Protection | Recommended MS116 4.00 ... 10.00 |
| Integrated Electronic Overload | No |
| Adjustable Rated Motor Current I_e | No % |
| Starting Capacity at Maximum Rated Current I_e | 4xle for 6s |
| Ramp Time | During Start 1 ... 10 second [unit of time] During Stop 0 ... 20 second [unit of time] |
| Initial Voltage During Start | 40 ... 70 % |
| Step Down Voltage Special Ramp | 100 ... 60 % |
| Current Limit Function | No |
| Switch for Inside Delta Connection | No |
| Run Signal Relay | Yes |
| By-pass Signal Relay | No |
| Fault Signal Relay | No |
| Overload Signal Relay | No |
| Signal indication completed start ramp (LED) | Green |
| Signal indication ready to start/standby ON (LED) | Green |
| Signal indication running R (LED) | Green |
| Signal indication ramping up/down (LED) | Green |
| Number of Starts Per | 10 |

Hour at 3.5*Ie for 7 sec.
50% ON Time 50% OFF
Time

| | |
|-------------------------------------|---|
| Communication | FiledBusPlug(Optional) |
| Degree of Protection | acc. to IEC 60529, IEC 60947-1, EN 60529 Main Terminals IP20 |
| Terminal Type | Screw Terminals |
| Connecting Capacity Main Circuit | Rigid 1/2x0.75 ... 2.5 mm ² |
| Connecting Capacity Control Circuit | Rigid 1/2 x 0.75 ... 2.5 mm ² |
| Connecting Capacity Supply Circuit | Rigid 1/2x0.75 ... 2.5 mm ² |
| Tightening Torque | Main Circuit 1 N·m Supply Circuit 1 N·m Control Circuit 1 N·m |
| Product Main Type | PSR6 |

Environmental

| | |
|-------------------------|---|
| Ambient Air Temperature | Storage -40 ... +70 °C Operation -25 ... +60 °C |
| RoHS Status | Following EU Directive 2002/95/EC August 18, 2005 and amendment |

Certificates and Declarations (Document Number)

| | |
|-----------------------------------|-----------------|
| Declaration of Conformity - CE | 1SFA1-86 |
| Environmental Information | 1SFC132038D0201 |
| Instructions and Manuals | 1SFC132030M0001 |
| RoHS Information | 1SFC132031D0202 |

Container Information

| | |
|-----------------------------------|---------------|
| Package Level 1 Width | 51 mm |
| Package Level 1 Depth / Length | 156 mm |
| Package Level 1 Height | 124 mm |
| Package Level 1 Gross Weight | 0.55 kg |
| Package Level 1 EAN | 7320500338209 |
| Package Level 1 Units | 1 piece |
| Package Level 2 Units | 1 piece |

Classifications

| | |
|----------------------------|---|
| Object Classification Code | Q |
| ETIM 4 | EC002572 - Electronic motor control and protection device |
| ETIM 5 | EC002572 - Electronic motor control and protection device |
| ETIM 6 | EC002572 - Motor management device |
| UNSPSC | 39121521 |

Categories

Drives → Softstarters → Softstarters → PSR Softstarters → PSR6

