

PRODUCT-DETAILS

E2.2N/MS 1250 3p F HR

E2.2N/MS 1250 3p F HR



General Information

Extended Product Type	E2.2N/MS 1250 3p F HR
Product ID	1SDA073406R1
EAN	8015644772567
Catalog Description	E2.2N/MS 1250 3p F HR
Long Description	C.BREAKER SWITCH-DISCONNECTOR SACE EMAX2 E2.2N/MS 1250 FIXED THREE-POLE WITH TERMINALS REAR HORIZONTAL

Ordering

EAN	8015644772567
Minimum Order Quantity	1 piece
Customs Tariff Number	85362090

Dimensions

Product Net Width	276 mm
Product Net Height	371 mm
Product Net Depth / Length	270 mm
Product Net Weight	41 kg

Container Information

Package Level 1 Units	1 piece
Package Level 1 Width	515 mm
Package Level 1 Height	610 mm
Package Level 1 Depth / Length	515 mm
Package Level 1 Gross Weight	46 kg
Package Level 1 EAN	8015644772567

Additional Information

Current Type	AC
Electrical Durability	Ue =< 440 V 15000 cycle Ue = 500 ... 690 V 15000 cycle 30 cycles per hour
Mechanical Durability	25000 cycle 60 cycles per hour
Number of Poles	3
Power Loss	83 W
Product Main Type	SACE Emax 2
Product Name	Switch Disconnecter
Product Type	Switch Disconnecter
Rated Current (I _n)	1250 A
Rated Voltage (U _r)	690 V
Rated Impulse Withstand Voltage (U _{imp})	12 kV
Rated Insulation Voltage (U _i)	AC 1000 V
Rated Operational Voltage	690 V AC
Rated Short-time Withstand Current (I _{cw})	for 1 s 66 kA for 3 s 50 kA
Rated Uninterrupted Current (I _u)	1250 A
Standards	IEC
Sub-type	E2.2
Terminal Connection Type	Rear flat Horizontal
Version	F

Certificates and Declarations (Document Number)

Data Sheet, Technical Information	1SDC200023D0209
Declaration of Conformity - CE	1SDL000165R0020
Environmental Information	Not Available
Instructions and Manuals	1SDH001000R0002

Classifications

ETIM 4	EC000228 - Power circuit-breaker for trafo/generator/installation prot.
ETIM 5	EC000228 - Power circuit-breaker for trafo/generator/installation prot.
ETIM 6	EC000216 - Switch disconnecter
ETIM 7	EC000216 - Switch disconnecter
Object Classification Code	Q

Categories

Low Voltage Products and Systems → Circuit Breakers → Air Circuit Breakers → Emax 2

