

PRODUCT-DETAILS

E6.2H/MS 5000 3p WMP

E6.2H/MS 5000 3p WMP



General Information

Extended Product Type	E6.2H/MS 5000 3p WMP
Product ID	1SDA073510R1
EAN	8015644773601
Catalog Description	E6.2H/MS 5000 3p WMP
Long Description	MOVING PART FOR C.BREAKER SWITCH-DISCONNECTOR SACE EMAX2 E6.2H/MS 5000 THREE-POLE

Ordering

EAN	8015644773601
Minimum Order Quantity	1 piece
Customs Tariff Number	85362090

Dimensions

Product Net Width	803 mm
Product Net Height	425 mm
Product Net Depth / Length	383 mm
Product Net Weight	120 kg

Container Information

Package Level 1 Units	1 piece
Package Level 1 Width	515 mm
Package Level 1 Height	610 mm
Package Level 1 Depth / Length	1000 mm
Package Level 1 Gross Weight	129 kg
Package Level 1 EAN	8015644773601

Additional Information

Current Type	AC
Electrical Durability	Ue = < 440 V 3000 cycle Ue = 500 ... 690 V 2000 cycle 10 cycles per hour
Mechanical Durability	12000 cycle 60 cycles per hour
Number of Poles	3
Power Loss	850 W
Product Main Type	SACE Emax 2
Product Name	Switch Disconnecter
Product Type	Switch Disconnecter
Rated Current (I _n)	5000 A
Rated Voltage (U _r)	690 V
Rated Impulse Withstand Voltage (U _{imp})	12 kV
Rated Insulation Voltage (U _i)	AC 1000 V
Rated Operational Voltage	690 V AC
Rated Short-time Withstand Current (I _{cw})	for 1 s 100 kA for 3 s 100 kA
Rated Uninterrupted Current (I _u)	5000 A
Standards	IEC
Sub-type	E6.2
Version	W

Certificates and Declarations (Document Number)

Data Sheet, Technical Information	1SDC200023D0209
Declaration of Conformity - CE	1SDL000165R0022
Environmental Information	Not Available
Instructions and Manuals	1SDH001000R0002

Classifications

ETIM 4	EC000228 - Power circuit-breaker for trafo/generator/installation prot.
ETIM 5	EC000228 - Power circuit-breaker for trafo/generator/installation prot.
ETIM 6	EC000216 - Switch disconnecter
ETIM 7	EC000216 - Switch disconnecter
Object Classification Code	Q
WEEE Category	4. Large Equipment (Any External Dimension More Than 50 cm)

Categories

Low Voltage Products and Systems → Circuit Breakers → Air Circuit Breakers → Emax 2

