

PRODUCT-DETAILS

# FA4N/MS 2500 3p WMP

## FA4N/MS 2500 3p WMP



### General Information

Extended Product Type	FA4N/MS 2500 3p WMP
Product ID	1SDA080488R1
EAN	8015644870164
Catalog Description	FA4N/MS 2500 3p WMP
Long Description	MOVING PART FOR C.BREAKER SWITCH-DISCONNECTOR FORMULA AIR FA4N/MS 2500 THREE-POLE

### Ordering

EAN	8015644870164
Minimum Order Quantity	1 piece
Customs Tariff Number	85362090

### Dimensions

Product Net Width	425 mm
Product Net Height	425 mm
Product Net Depth / Length	383 mm
Product Net Weight	85 kg

### Container Information

Package Level 1 Units	1 piece
Package Level 1 Width	515 mm
Package Level 1 Height	610 mm
Package Level 1 Depth / Length	615 mm
Package Level 1 Gross Weight	67 kg
Package Level 1 EAN	8015644870164

## Additional Information

Current Type	AC
Electrical Durability	20 cycles per hour
Mechanical Durability	20000 cycle 60 cycles per hour
Neutral Pole Current ([% I <sub>n</sub> ])	100 %
Number of Poles	3
Product Main Type	Formula Air
Product Name	Switch-disconnector
Product Type	Switch-disconnector
Rated Current (I <sub>n</sub> )	2500 A
Rated Voltage (U <sub>r</sub> )	690 V
Rated Impulse Withstand Voltage (U <sub>imp</sub> )	12 kV
Rated Insulation Voltage (U <sub>i</sub> )	AC 1000 V
Rated Operational Voltage	690 V AC
Rated Short-time Withstand Current (I <sub>cw</sub> )	for 1 s 50 kA for 3 s 36 kA
Rated Uninterrupted Current (I <sub>u</sub> )	2500 A
Standards	IEC
Sub-type	FA4
Terminal Connection Type	Withdrawable Circuit-Breakers
Version	W

## Certificates and Declarations (Document Number)

Data Sheet, Technical Information	1SDC200044D0201
Declaration of Conformity - CE	9AAK10103A1376
Environmental Information	Not Available
Instructions and Manuals	1SDH001600R0002

## Classifications

ETIM 6	EC000216 - Switch disconnector
ETIM 7	EC000216 - Switch disconnector
Object Classification Code	Q
WEEE Category	5. Small Equipment (No External Dimension More Than 50 cm)

---

## Categories

---

Low Voltage Products and Systems → Circuit Breakers → Air Circuit Breakers → Formula AIR

